

# User Guide

---



## Model – SC510N2-L HDMI

## 1、 Introduction

SC510N2 SDI is a high-quality, high-performance capture device. It supports up to 4 channels of video inputs with SDI connectors.

## 2、 Specification

<b>Model</b>	SC510 N2-L HDMI
<b>Max. FPS</b>	120/100fps @ 1920x1080p
<b>Dimension</b>	140 x 64.41 (mm)
<b>Interface</b>	PCIe x4
<b>Video Input</b>	2 x HDMI
<b>Display Video Format</b>	YV12,NV12,YUY2,RGB24,RGB32
<b>Display Video Resolution</b>	1920×1080p@60/50fps 1920×1080p@30/25/24fps 1920×1080i@60/50fps 1280×720p@60/50fps 1280×1024p@60fps 1280×960p@60fps 1024×768p@60fps 800×600p@60fps 720×576p@50fps 720×576i@50fps 720×480p@60fps 720×480i@60fps 640×480p@60fps
<b>Recording Video Resolution</b>	1920×1080p@60/50fps 1920×1080p@30/25/24fps 1920×1080i@60/50fps 1280×720p@60/50fps 1280×1024p@60fps 1280×960p@60fps 1024×768p@60fps 800×600p@60fps 720×576p@50fps 720×576i@50fps 720×480p@60fps 720×480i@60fps

<b>Audio Input</b>	2 x embedded HDMI
<b>Audio Format</b>	Stereo / 16-bit / 32000-48000Hz
<b>WatchDog</b>	Yes
<b>SDK</b>	VC++ / .NET / VB / V4L2
<b>System Requirement</b>	
<b>OS Support</b>	Windows XP / Vista / Windows 7,8,10 Linux 2.6.14 or Higher ( 32-bit and 64-bit )

### 3、 Packing List

Item	Amount
SC510 N2 HDMI Capture Card	1 (piece)
Watchdog cable	1 (piece)
USB stick or CD with driver	0 (piece)

### 4、 Hardware Installation

#### Before You proceed

Please note below precautions before any install/uninstall operations:

- ✓ ALWAYS turn off the system before hardware installation/un-installation.
- ✓ ALWAYS unplug the power cord from the wall outlet/socket before hardware installation/un-installation.
- ✓ ALWAYS touch a safely grounded object or metal object before touching the device.
- ✗ DO NOT touch any devices before the system is fully off.
- ✗ DO NOT touch any electrical and semiconductor components on the device, especially ICs on board.

#### 4.1 Card and Driver Installation

Step 1: Turn off the system and unplug power cord from wall outlet/socket.

Step 2: Remove the computer system case cover.

Step 3: Plug capture device into an available PCIe slot on motherboard.

Step 4: After hardware installation is completed, then install the driver.

DRIVER can be downloaded from (vMix & DirectShow)

<http://www.yuan.com.tw/en/market/software/vmixdriver/vmixdriver.htm>

## **4.2 Signal Source Connection Diagram**

## **4.3 Watchdog cable Installation (optional)**

Watchdog function is to reset the PC automatically when the system is crashed on an unknown error.